


SIGNAL CORPS
REPAIR STANDARD

NO. REP-890
ISSUE NO. 1

REPAIRED EQUIPMENT STANDARD
FOR
RADIO RECEIVER SECTION OF RADIO SET AN/PRC-5

PROJECT 4422D

31 March 1954



PROPERTY OF TECHNICAL LIBRARY
FOR REFERENCE

NOT TO BE CHECKED FROM THIS ROOM

SIGNAL CORPS ENGINEERING LABORATORIES

FORT MONMOUTH, N. J.

Copy 1

SIGNAL CORPS ENGINEERING LABORATORIES
FORT MONMOUTH, NEW JERSEY

31 March 1954

Signal Corps Repair Standard #890 has been prepared under the supervision of PM&E Division and is published for the information and guidance of all concerned. Suggestions or criticisms relative to the form, contents, purpose, or use of this publication should be referred to Signal Corps Engineering Laboratories, Fort Monmouth, N.J., Attn: Chief, Maintenance Engineering Branch.

F. F. UHRHANE
Colonel, Signal Corps
Commanding

OFFICIAL:
MAX P. BUTLER
Capt, SigC
Adjutant

DISTRIBUTION:
Special

PREFACE

Signal Corps Repair Standards (formerly Signal Corps Repaired Equipment Requirements) are prepared by the Maintenance Engineering Branch, Procurement-Maintenance Engineering Division, Signal Corps Engineering Laboratories, and cover various items of signal equipments which are subject to repair, test and inspection. These repair standards are documents which set forth the specific repair requirements and test standards to be applied to the individual equipments being repaired and tested.

Signal Corps Repair Standards are prepared for the specific use of the fifth echelon Signal Repair Shops in repairing and determining the quality and acceptability of repaired signal equipments covered by these standards. The use of Signal Corps Repair Standards is recommended as a guide and reference for any agency having occasion to repair, test or inspect an item of signal equipment for which a repair standard has been prepared.

Signal Corps Repair Standard No. REP-1001 is a general standard and is subsidiary to any individual standard prepared. No individual standard is to be considered complete in itself, but is to be used in conjunction with Signal Corps Repair Standard No. REP-1001, "General Standards for Repaired Signal Equipment."

Reports of any discrepancies or any other constructive comments bearing upon this repair standard are invited. A series of Comments and/or Notes pages will be found in the back of this standard which are designed to facilitate reporting any inaccuracies noted. All such reports or comments as well as requests for additional copies, should be addressed to:

COMMANDING OFFICER
Signal Corps Engineering Laboratories, SIGEL-PMM-3
Fort Monmouth, New Jersey.

TABLE OF CONTENTS

Section	Text	Paragraph	Page
	Preface		II
I.	Statement Covering Applicability		1
II.	Applicable References		1
	Repair Standards	A	1
	Technical Publications	B	1
III.	Test And Additional Equipment . .		2
	Test Equipment	A	2
	Additional Equipment	B	2
IV.	Test Data Sheet for Radio Receiver Section of Radio Set AN/PRC-5 . .		3

REPAIRED EQUIPMENT STANDARD
FOR
RADIO RECEIVER SECTION OF RADIO SET AN/PRC-5

I. STATEMENT COVERING APPLICABILITY

This repair standard covers inspection requirements to be used in determining the quality and acceptability of repaired Radio Receiver Section of Radio Set AN/PRC-5. This standard must be used in conjunction with Signal Corps Repair Standard No. REP-1009, Radio Receivers (AM), General Standards which form a part of this standard. Its use is mandatory in the Maintenance Divisions of Signal Depots and the Signal Sections of General Depots. The use, insofar as limitations of test and calibration equipment permit, is highly recommended for all Signal Repair organizations.

II. APPLICABLE REFERENCES

A. Repair Standards. Applicable paragraphs of the repair standards listed below form a part of this standard:

Title	Number	Paragraph
1. General Standards REP-1001 for Repaired Signal Equipment		
2. Class "C" Receiver and Low Power Transmitter Vacuum Tubes	REP-242	B4, D1, D2, D3

Meters showing signs of sluggishness or suspected of incorrect indications shall conform to the requirement of all paragraphs of REP-85.

B. Technical Publications. The following technical publications form a part of this standard to the extent referenced herein:

Title	Number
Technical Manual Radio Set AN/PRC-5	TM 11-265

NOTE: All applicable Modification Work Orders pertaining to this equipment shall be performed.

III. TEST AND ADDITIONAL EQUIPMENT

The following equipments, or suitable equivalents of known accuracy, will be employed in determining compliance with the requirements of this Signal Corps Repair Standard and will be capable of conforming to their respective Repair Standards:

A. Test Equipment

	Equipment	Stock Number	Number Used	REP
1.	Multimeter TS-352/U	3F4325-352	1	420
2.	AN/URM-25B	3F3901.2-25B	1	-
3.	Frequency Meter FR-4/U	3F2435-4	1	-

B. Additional Equipment

	Equipment	Stock Number	Number Used	REP
1.	Resistor, fixed: 10,000 ohms	3RC30BF103J	1	-
2.	Resistor, fixed: 390 ohms, 1/2 w	3RC30BF391J	1	-
3.	Headset HS-30	2B830 ()	1	-

TEST DATA SHEET
FOR
RADIO RECEIVER OF RADIO SET AN/PRC-5

IV: GENERAL CONDITIONS

1. Dummy Antenna 390 ohms.
2. Output Load 10,000 ohms across phones jack ref-
symbol J2.
3. Standard Output 10 volts.
4. Supply Voltage 110/220v AC, ± 10 volts.
5. RF signal modulation 400 cps.

Test	Specified Value			Measured Value		
1. Sensitivity (uv)	High	Middle	Low	High	Middle	Low
Standard noise output	Band 1, 10	10	10			
3.1 voltage ratio	Band 2, 25	25	25			
1	Band ,					
2. CW Sensitivity	Band 1, 5	5	5			
	Band 2, 10	10	10			
	Band ,					
3. Selectivity:	Input	Bandwidth		Bandwidth		
Standard input	20 uv	3 kc min,				
10 microvolts at		7 kc max				
5,000 kc	100 uv	20 kc max				
	1000 uv	40 kc max				
	10,000 uv	80 kc max				
				Min	Max	
4. Frequency Range:	Band 1	4500 kc to 8000 kc		kc	kc	
	Band 2	8000 kc to 16000 kc		kc	kc	
5. Calibrations and Resetability:	Frequency					
	Band 1	55 kc 5000-8000 kc		kc	kc	
	Band 2	55 kc 8000-16000 kc		kc	kc	

TEST DATA SHEET (CONTD.)

Test	Specified Value	Measured Value
6. Frequency drift: (in 30 min at 5,000 kc)	± 15 kc	_____ kc
7. Special Tests	The audio output shall be not less than 16 volts with inputs of 100,1000, 10,000 and 100,000 microvolts.	Satisfactory _____ Not Satisfactory _____
8. Operation Check		
Quality of Signals (Voice and CW)	Band 1 Satisfactory Band 2 Satisfactory	_____ _____
Visual tuning	Function properly	_____
Controls	Function properly	_____
Vibration	No effect	_____

Tests listed in REP-1009 but which do not appear on this
Test Data Sheet do not apply to Radio Receiver Section of
Radio Set AN/PRC-5.

SIGNAL CORPS
REPAIR STANDARD

NO. REP - _____
ISSUE NO. _____

COMMENTS AND / OR NOTES

SIGNAL CORPS
REPAIR STANDARD

NO. REP - _____

ISSUE NO. _____

COMMENTS AND / OR NOTES

SCEL

Signal Corps Repair Standard REF-890

AUTHOR

TITLE

31 March 1954

Copy 1

DATE DUE