MH-31 GRUNDMANN MOD & FTDX10 KNOB SETTINGS

(DX/CONTEST SETUP)



TONE SWITCH
SET TO POSITION 2 (SHARP)



MIC GAIN 10 - 15



PROC LEVEL 10 - 15



AMC LEVEL LOWER VALUE 15 - 25 (HIGH COMPRESSION)

TX AUDIO PROFILE & P-EQ MENU

(BANDWIDTH: 300-2700Hz)

AUDIO FREQUENCY SPECTRUM CURVE



P Parametric EQ			
MENU ITEM	FREQUENCY	LEVEL	BWTH
P EQ1 (Low)	300Hz	-6dB	BW 4
P EQ2 (Mid)	1200Hz	+3dB	BW 5
P EQ3 (High)	2400Hz	+2dB	BW 5

***Note:** Lower AMC level pushes the peak limiter down, drastically increasing talk power. Monitor ALC/COMP strictly.