

## How to Make a Telephone Call with a Barrett 250.

\*Select the required Channel.



\*Press Button.

\*Punch in the base's "4 digit Telephone Beacon Number" via the keypad.



\*Press Button.

\*Now use the keypad to punch in the phone number you require with area code.



\*Now press the Button.-Your radio will now go quiet for about 10 seconds while it sends the telcall information to the base.

\*If all is well, you should now hear some revert tones come back from the base-These tones sound different to a selcall revert. They sound more like the tones you hear when making an international call on your home phone—You should then start to hear the normal ring tone of your dialled number about 10 seconds later.



\*Note that if a mistake is made during the above process, press the Button and re-enter the required information.

## How to hang up a Telephone call.



\*Press button, you should now see the base's Telephone beacon number on the screen.



\*Press to complete the hang up sequence. You should hear some tones come back from the base, confirming that the disconnection has been successful.

Note: Hanging up the phone from the radio end is notoriously unreliable (This relates to all makes and models of HF radio). A much more reliable option is the get the person on the other end of the phone to punch "99" on their keypad.

Note that most SB250 radios built after 1991 had the direct dial telcall option fitted as a standard feature. Earlier model 250s may need to be upgraded to make direct dial calls.